

LED EMERGENCY DRIVER SERIES

SES-EM08N



Technical Specifications

Size:	9.3" L x 2" W x 1.8" D
Max Watts:	8W
Compatible With:	Up to 40W
Compatibility:	Internal Non-Isolated Driver Tube Lights, Retrofit Downlights (Must be tested, does not work with on-board drivers)
Driver Output:	400mA DC95V
Voltage:	AC100-277V
Power Time:	>90 Minutes
Recharge Time:	24 Hours
Battery:	Ni-MH
IP Rating:	IP42
Included:	Test Switch, Charge Indicator
Operating Temp:	32°F - 122°F
Life Expectancy:	5 Years
Protection:	Over Voltage, Low Voltage, Over Temperature




Features

When the electrical power source to the attached fixture is terminated, an emergency pack detects the power outage and automatically switches to emergency mode. The charging indicator will be off at this point. The LED fixture is illuminated for a minimum of 90 minutes. When power is restored the emergency pack switches back to standby mode and begins recharging.



Dimensions



Model Numbers

#10906 SES-EM08N