



# EVC

## EV FAST CHARGER

Project: \_\_\_\_\_ Type: \_\_\_\_\_

Name: \_\_\_\_\_ Date: \_\_\_\_\_

<b>Power</b>	120 KW, 240KW
<b>Input Voltage</b>	380-480VAC
<b>Input Frequency</b>	50/60Hz
<b>Output Voltage</b>	200-1000VDC
<b>Max Output Current of Single Gun</b>	200A
<b>Voltage Stabilization Accuracy</b>	±0.5%
<b>Steady Current Accuracy</b>	±1%
<b>Power Factor</b>	≥0.95
<b>Heat Dissipation Method</b>	Forced air cooling
<b>Input Wire Harness</b>	TN-S, L1, L2, L3, N, PE
<b>Charging Method</b>	Off line card swiping, password charging, online card swiping, APP code scanning
<b>Communication Method</b>	Ethernet WiFi Bluetooth 4G
<b>Indicator Light</b>	<b>Standby:</b> green light always on; <b>Charging:</b> the green light flashes; <b>Fault:</b> the red light always on
<b>Display Screen</b>	7-inch touch screen
<b>Advertising Screen</b>	55-inch LCD advertising screen (support WIFI, Ethernet, 4G)
<b>Installation Mode</b>	Floor-standing style
<b>Number of Interfaces</b>	2 (line length 5m), customizable gun line ≤10m
<b>Size (H*W*D)</b>	74.8" X 28.4" X 24.4" (1900mmX720mmX-620mm)
<b>Product Weight</b>	350KG
<b>Housing Material</b>	Galvanized sheet
<b>Storage Temperature</b>	-22 to 158F°
<b>Working Temperature</b>	-4 to 131F°
<b>Relative Humidity</b>	≤95%
<b>Protection Level</b>	3A
<b>Usage Occasion</b>	Household and commercial charging



### Common Stock Models:

Item #	Model #
35000	SES-EVC-DC240KW
35001	SES-EVC-DC120KW

<b>Leakage Protection</b>	Yes
<b>Overvoltage Protection</b>	Yes
<b>Low-Voltage Protection</b>	Yes
<b>Overcurrent Protection</b>	Yes
<b>Short Circuit Protection</b>	Yes
<b>Full Stop Charging</b>	Yes
<b>Custom LOGO</b>	Yes
<b>Customized Appearance</b>	Yes
<b>Custom Specification</b>	Yes