

**EXC2RWE****EMERGENCY
& EXIT COMBO
SIGN**

Project: _____ Type: _____

Name: _____ Date: _____



Size	12" W x 11.7" H x 3.8" D	Lumens	>220lm
Watts	4.2W	CCT	6500K
Voltage	120/277V	IP Rating	IP20
Dimming	Non-Dimming	Materials	Thermoplastic ABS
Backup Time	≥90 minutes	Finish	White
Mounting	Wall, Ceiling	Lens	Clear
Sides	Double Sided	Lifespan	50,000 Hours

SARIN EMERGENCY & EXIT COMBO SIGNS are designed to show an exit during a crisis. It has two adjustable flood light arms to add more illumination during a power outage. When this unit stops receiving power, it automatically activates and shines brightly for up to 90 minutes before needing to recharge again from its original power source.

These emergency lights are ideal in cases where lighting may no longer be available, black out situations, and any unforeseen events, guiding occupants to safety. The housing is made out of thermoplastic materials that are flame retardant and perfect for proactive business owners.

OVERVIEW

CCT: 6500K**Applications:** IP20**Efficacy:** 60lm/W**Dimming:** Non-Dimming**Lens Type:** Clear**Lifespan:** 50,000 Hours**Warranty:** 3 Years

FEATURES

- 90 minutes of battery life that automatically activates when power loss is detected.
- Nickel Cadmium battery recharges when power is flowing, charging to full in approximately 24 hours.
- Lighting fixtures are hand-adjustable for multiple angle coverage.





EXC2RWE

EMERGENCY & EXIT COMBO SIGN

Project: _____ Type: _____

Name: _____ Date: _____

ORDER FORM:

(*) Special Order/Not Commonly Stocked

Custom Model Assembly

Fixture	CCT	Watts	Backup Time	Voltage
<input checked="" type="checkbox"/> EXTEC2	<input type="checkbox"/> 6500K	<input checked="" type="checkbox"/> 4.2W	<input checked="" type="checkbox"/> ≥90 min.	<input checked="" type="checkbox"/> 120/277V

SES-EXC2RWE
Example Model Number

SES — EXC2RWE — 6500K — 4.2W — ≥90 min. — 120-277V

Quantity

Fixture

CCT

Watts

Backup Time

Voltage

Common Stock Models:

Item #	Model #
11147	SES-EXC2RWE

DIMENSIONS:

